



Configuration

Related products: S2928F, S3700 Series, S5612, S5800 Series, S8500 Series, S9500 Series

IGMP Proxy Commands

Table of Contents

Chapter 1 IGMP Proxy Commands.....	1
1.1 ip igmp-proxy enable	1
1.2 ip igmp-proxy agent-vlan client-vlan map	2
1.3 ip igmp-proxy source svlan sport	2
1.4 show ip igmp-proxy mcache	3
1.5 show ip igmp-proxy	4
1.6 debug ip igmp-proxy	5

Chapter 1 IGMP Proxy Commands

IGMP-proxy commands include:

Ip igmp-proxy

ip igmp-proxy agent-vlan client-vlan map

ip igmp-proxy source svlan sport

show ip igmp-proxy mcache

show ip igmp-proxy

debug ip igmp-proxy

1.1 ip igmp-proxy enable

Syntax

ip igmp-proxy enable

no ip igmp-proxy enable

To enable or disable `IGMP proxy`, run **ip igmp-proxy enable**. To resume the default value, run **no ip igmp-proxy enable**.

Parameter

Parameter	Description
N/A	

Default value

The IGMP proxy is disabled by default.

Remarks

N/A

Example

The following example shows how to enable the IGMP proxy:

```
switch_config# ip igmp-proxy enable
```

```
switch_config#
```

1.2 ip igmp-proxy agent-vlan client-vlan map

Syntax

```
ip igmp-proxy agent-vlan avlan_map client-vlan map cvlan_map
```

```
no ip igmp-proxy agent-vlan avlan_map client-vlan map cvlan_map
```

Parameter

Parameter	Description
<i>avlan_map</i>	A g e n t V L A N
<i>cvlan_map</i>	Customer VLAN

Default value

N/A

Remarks

1. The represented VLAN cannot be configured before *vlan* is designated by *avlan_map*; also, the agent VLAN cannot be configured before *cvlan_map*.
2. The represented and agent VLANs must accept the control of IGMP-Snooping.

Example

The following example shows how to set *vlan2* to be the agent *vlan* of *vlan1*.

```
switch_config# ip igmp-proxy agent-vlan 2 client-vlan map 1
switch_config#
```

1.3 ip igmp-proxy source svlan sport

Syntax

```
ip igmp-proxy source multi_ip src_ip svlan vlan_id sport intf_name
```

```
no ip igmp-proxy source multi_ip src_ip svlan vlan_id sport intf_name
```

To set the entries of the static multicast source, run the above-mentioned command.

Parameter

Parameter	Description
multi_ip	Multicast IP address
src_ip	Multicast source's IP address
vlan_id	Multicast source VLAN
intf_name	Physical port of the multicast source

Default value

N/A.

Remarks

Only when there are multicast source entries can IGMP-proxy work normally. What is mentioned here is to add static multicast source entries.

Example

The following example shows how to add a multicast source entry with 234.5.6.7 as its static multicast address, 1.2.3.4 as its source address, 2 as its source VLAN and gigabit portg0/1 as its source port.

```
switch_config# ip igmp-proxy source 234.5.6.7 1.2.3.4 svlan 2 sport g0/1
switch_config#
```

Note:

The SVLAN mentioned here is the multicast source VLAN and the vlan ID of SVLAN cannot be that of represented VLAN.

1.4 show ip igmp-proxy mcache

Syntax

show ip igmp-proxy mcache [*delete | nonsync | sync | static*]

Parameter

Parameter	Description
<i>delete</i>	Displays those entries of which hardware caches are deleted but software caches do not time out.
<i>nonsync</i>	Displays those entries that have been processed but not yet synchronized to the hardware cache.

<i>sync</i>	Displays those entries already in the hardware cache.
<i>static</i>	Displays the entries of the IGMP-proxy static multicast cache.

Default value

All entries are to be displayed if no filtration conditions are specified.

Remarks

The multicast source entries of IGMP-proxy are displayed.

Example

The following example shows how to display the information about the IGMP-proxy multicast source.

Switch# **show ip igmp-proxy mcache**

Codes: '+' synchronization, '-' deleted, 'S' static

'^' unsynchronization

Item 1: Group 225.1.1.2

+(192.168.213.163, 2, G3/24)

VLAN 3,4

1.5 show ip igmp-proxy

Syntax

show ip igmp-proxy

Parameter

N/A

Default value

N/A

Remarks

This command is used to display the configurations about IGMP proxy.

Example

The following example shows how to display the configurations of IGMP proxy.

```
switch#show ip igmp-proxy
```

Global IGMP proxy configuration:

Globally enable : Enable

Agent: vlan 2, it has been allocated

Client static : vlan 1

Client auto : vlan

Agent: vlan 3, it has been allocated

Client static : vlan 1

Client auto : vlan

Globally clients list

Client : vlan 1, it has been allocated

Static Multi-source list

Static Source : No Static Source

switch#

1.6 debug ip igmp-proxy

Syntax

debug ip igmp-proxy [*error* | *event* | *packet*]

no debug ip igmp-proxy [*error* | *event* | *packet*]

Parameter

Parameter	Description
<i>event</i>	Debugs the IGMP-snooping event.
<i>packet</i>	Debugs the reception and transmission of IGMP-snooping.
<i>error</i>	Debugs the IGMP-snooping errors.

Default value

N/A

Remarks

This command is used to enable or disable the debugging & printing switch of IGMP-proxy.