



## Configuration

Related products: S2928F, S3700 Series, S5612, S5800 Series, S8500 Series, S9500 Series

## Port Mirroring Configuration Commands

# Table of Contents

Chapter 1 Configuring Port Mirroring Commands.....	1
1.1 Port Mirroring Configuration Commands .....	1
1.1.1 mirror .....	1
1.1.2 show mirror.....	1

# Chapter 1 Configuring Port Mirroring Commands

## 1.1 Port Mirroring Configuration Commands

The following are port mirroring configuration commands:

- mirror
- show mirror

### 1.1.1 mirror

#### Description

**[no] mirror session *session\_number* {destination {interface *interface-id* } | source {interface *interface-id* [, | -] [both | rx | tx ]}}**

It is used to configure the command.

#### Parameters

Parameter	Description
<i>session_number</i>	Number of port mirroring, whose value is 1
<i>destination</i>	Information about the destination port mirroring
<i>source</i>	Information about the mirrored port
<i>both   rx   tx</i>	Data flow that will be mirrored  <b>rx</b> means that the input data is mirrored. <b>tx</b> means that the output data is mirrored. <b>both</b> means that input and output data are mirrored.

#### Instruction

The command is configured in global configuration mode. S2524GT, S2524GX and S2516 only support the tx mirroring output of one port and the **both** dataflow of another port.

#### Example

Port g0/2 functions as the output mirror of port g0/1.

```
Switch(config)# mirror session 1 destination interface g0/2
```

```
Switch(config)# mirror session 1 source interface g0/1 tx
```

### 1.1.2 show mirror

#### Description

**show mirror [session *session\_number*]**

It is used to display the port mirroring information.

**Parameter**

Parameter	Description
<i>session_number</i>	Number of port mirroring, whose value is 1

**Default**

None

**Instruction**

It is used to display the port mirroring information.

**Example**

All port mirroring information is displayed.

```
Switch# show mirror
```

```
Session 1
```

```
-----
```

```
Source Ports:
```

```
RX Only: g0/3
```

```
TX Only: None
```

```
Both: None
```

```
Source VLANs:
```

```
RX Only: None
```

```
TX Only: None
```

```
Both: None
```